

LED Light Tech™ 1-3 hour- 30 Watt Battery Back up

SPECIFICATIONS:

- Watts: 30
- Input Voltage: 100-277VAC
- Emergency Run Time: 1-3 hours



FEATURES AND BENEFITS:

- Reverse charging is not acceptable.
- Charge before use. The battery is delivered in half-charged state.
- Do not short circuit the battery.
- Do not incinerate or destroy the battery.
- Do not solder directly to the battery.
- The life expectancy may be reduced if the battery is subjected adverse conditions: extreme temperature, deep cycling, excessive over-charge / over-discharge.
- Store the battery in a cool dry place.

 BATTERY	EMERGENCY KIT	
TEST INDICATOR RED: CHARGING GREEN: POWER YELLOW: TROUBLE		
 PAY ATTENTION TO SAFETY HIGH RISK WARNING	INPUT: AC 100-277V 50/60HZ LIGHT SOURCE: MAX 30W LED BATTERY: Ni-Cd 12V EMERGENCY DURATION: 1-3 HOURS	

Input Voltage	AC 100~277V
Frequency	50/60HZ
Battery	Ni-Cd 12V
Charge time	24~72 hours
Emergency time	1~3 hours
Operating Temp.	-10 ~ +5011
IP Grade	IP20
Dimension of Inverter	29x40x206mm
Dimension of Battery	Customized
Light Source	MAX 30W LED Light
Emergency Brightness	90%
Work Mode	Maintain / Non-Maintain
Indicator Light	Red for Charging / Green for Power / Yellow for Trouble
Test Button	Available
Protection	Over-Charge / Over-Discharge

PRODUCT ORDER CODE: LLT-41-BBU-30

