

USER MANUAL

play  
back  
d e l a y





## Congratulations

on your purchase of **Play Back** delay, the intuitive, amazing-sounding tap-controlled delay pedal from T-Rex.

As its name suggests, **Play Back** gives you two great advantages over other delay pedals. First, you get tap control of your delay tempo – so you can adjust your tempo to fit any song, just by tapping along. Then, you get legendary T-Rex delay that you can fine tune via the **Play Back BITE** control.

In the T-Rex tradition, **Play Back** is quick to learn and easy to use. Just turn the page to get started.

## Play Back Controls

Your **Play Back** has five delay controls, plus the **TAP** tempo button. The first three controls – **DELAY**, **FEEDBACK**, **TONE** and **TIME** – are standard delay pedal controls:

The **DELAY** lets you adjust how loud your delayed signal is compared to the original note or chord you play on your guitar.

The **FEEDBACK** knob determines how many repetitions your pedal produces, or how long the delay effect continues.

The **TONE** control lets you take the top of your delayed repeats for an even more authentic vintage tone.

The **TIME** control lets you set the tempo of your delayed repetitions – from short slap-back to a long “spacey-sounding” echo.

The **BITE** knob lets you tune the sonic character of your delayed signal to match the style of music you’re playing or your own tastes. Turn it up for a dirtier, analogue-style delay sound.

Finally, the **TAP** button (bottom right) is an alternative **TIME** control that lets you set the tempo of your delay by simply tapping along to the beat. It means you can say goodbye to having to reach down and manually adjust your pedal.

# Technical Specification

Input Impedance @ 1KHz	Higher than 1M Ohm
Output Impedance @ 1KHZ	Lower than 1K Ohm
Power supply	9V DC (T-Rex FuelTank)
Power supply Voltage	9V DC
Current Draw @ 9V DC	85 mA
Maximum Input signal Vp/p	3Vp/p
Battery Type	9 V battery 6F22
Battery Life	30 - 60 min.
External connectors	Input Jack, Output Jack, 9V DC Jack
Controls	On/Off, Tap Tempo, Bite, Delay, Feedback, Time
Pedal size incl. knobs (W x H x D)	100 x 55 x 120 mm 3,9 x 2,2 x 4,7 inch
Weight excl. battery and packaging	0,335 kg / 11,8 oz

## T-REX WARRANTY CONDITIONS

T-Rex offers a 2-year warranty on all our products. In the unlikely event of a malfunction, please contact our technical support at [service@t-rex-effects.com](mailto:service@t-rex-effects.com) before sending us the product for repair. Read more about warranty conditions at [www.t-rex-effects.com/service](http://www.t-rex-effects.com/service)

## ABOUT T-REX

Based in Vejle, Denmark, T-Rex Engineering makes classic and signature effects pedals for the world's best musicians. Our approach blends hi-tech innovation with old-world craftsmanship – always in the service of killer tone.

## EU REGULATIONS • ENVIRONMENT PROTECTION

T-Rex accepts and follows the regulations and directives issued by the EU. We find these environment protecting regulations very good, and we are happy to follow them.



*Lars D. Jørgensen*

*Sebastian Jensen*



Lars Dahl-Jørgensen  
& Sebastian Jensen  
Founder & Owner

T-Rex Engineering ApS



[www.t-rex-effects.com](http://www.t-rex-effects.com)